

## **What's the meaning of DIY Lock?**

DIY Lock means do it by yourself, that is to say, this kind of lock without encoder and software, just use mastercard.

## **DIY RF Card Locks' User Direction**

**Step 1:** Put the Manage Card about 3cm near to the lock's indicator and both green and red lights will be flashing. Before the lights turn off, put the desired opening cards near to the indicator one by one to issue the opening card. Every time making a opening card, the lock will make a brief alarm to tell you the issue is successful.(Those cards do not be issued by this Manage Card on this lock can not open this lock).

**Step 2:** If any opening card is lost, put the Manage Card 3cm near to the indicator for one minute Both green and red lights will be flashing accompany with a long term alarm, all the opening cards including the lost card, can not open the lock. You have to follow up step 1 to re-issue the desired opening cards to use on this lock.

## **Emergency Key Machine User Direction (For DIY RF Card Lock).**

**Step 1:** Connect the Emergency Key Machine's line to the left small hole which locates underthe bottom of the front lock cover.

**Step 2:** Put Manage Card on Emergency Key Machine, turn on the switch to supply power for the lock. The green LED on the machine will be flashing, then put the opening card key to open the door. (Note: Please do remember to put the manage card on the machine before turn on the switch to supply power, otherwise, both green and red LED will be flashing and the machine will make a long term alarm to remind you it is failure to operate the lock)

**Step 3:** After opening the door by this machine, please turn off it to avoid any electricity consume.

### **DIY IC Card Locks' User Direction**

**Step 1:** Insert the Manage Card into the lock, you can insert opening cards one by one. You can use opening cards to open the lock.

**Step 2:** If any opening card is lost, insert the Manage Card into the lock three times continuously. The former lost opening cards cannot open the lock. You have to follow up Step 1 to re-issue the desired opening cards to use on this lock.